



DIGITAL SOUND LEVEL METER



Digital Sound Level Meter provides the convenience of digital readability. It is a precise and portable Meter for measurement of noise level in decible.

General Specifications :

- « Display : 18mrn LCD 3½ digits
- « Measurement 3 Range : 30—80 dB
50—100 dB
80—130 dB
- « Resolution : 0.1 dB
- « Accuracy : 0.7 dB - after calibration.
[Calibration point, 94 dB/1000 Hz.]
- « Power supply : 006P DC 9V battery (heavy duty type.)
- « Dimension : 205 x 80 x 35 mm
- « Weight : 280g (including battery).
- « Make : Taiwan

DIGITAL SOUND LEVEL METER

DIGITAL LUX METER

Wide Range, Portable type, Better Performance

FEATURES		
Auto zero adjustment		
LCD display provides low power consumption		
Compact, light-weight, and excellent operation		
LCD display can clearly read out even in high ambient light		
SPECIFICATIONS		
Display	13 mm (0.5") LCD (Liquid Display)	
Power Supply	150-200 hours in continious use.	
Range	Resolution	Accuracy (25 + 50C)
2,000 Lux	1 Lux	± (5% + 2d)
20,000 Lux	10 Lux	± (5% + 2d)
50,000 Lux	100 Lux	± (5% + 2d)
Standard Accessorius	Light Sensor1 pc	
	Instruction manual1 pc.	
	Carry Case1 pc.	



DIGITAL LUX METER



NANDA MILLAR COMPANY

Office : 32A, Chittaranjan Avenue, 2nd Floor, Kolkata-700 012. India. Tel : +91 33 2212 3530 / 3531 / 1783

Fax : +91 33 2212 2070. E-mail : nmc@nandagroup.com URL : www.nandagroup.com



An ISO 9001 : 2000 Registered Company